

电容式加速度传感器

|      |   |   |   |  |   |   |
|------|---|---|---|--|---|---|
|      |  |  |  |  |  |  |
| 型号   | LC-DR-001   | LC-DR-005   | LC-DR-050   | LC-DR-3001   | LC-DR-3005  | LC-DR-3050  |
| 编号   | CG0015  | CG0016  | CG0017  | CG0018   | CG0019  | CG0020  |
| 测量范围 | ±1g   | ±1g   | ±50g  | ±1g  | ±5g   | ±50g  |
| 灵敏度  | 1000±10% $mV/g$   | 200±10% $mV/g$  | 38±10% $mV/g$   | 1000±10% $mV/g$  | 200±10% $mV/g$  | 38±10% $mV/g$   |
| 频率响应 | 0~800Hz   | 0~800Hz   | 0~400Hz   | 0~800Hz  | 0~800Hz   | 0~400Hz   |
| 工作温度 | -40~+85℃  | -40~+85℃  | -40~+85℃  | -40~+85℃   | -40~+85℃  | -40~+85℃  |
| 供电方式 | +6~+16VDC   |   |   |  |   |   |
| 应用   | 测量低频振动信号，抗干扰好   |   |   |  |   |   |